



PHOENIX 200 POWER STATION



RENOGY PHOENIX 200 POWER STATION

Integrating a 189Wh high energy density battery pack in a compact housing, the Renogy PHOENIX 200 is ready to fulfil your off-grid electricity needs with no fuel or gasoline required. Equipped with multiple output ports, the PHOENIX 200 is dedicated to power different mobile electronics and small appliances simultaneously. Supporting versatile input options, the PHOENIX 200 can get recharged from a wall outlet, a car socket, or a solar panel. The built-in powerful LED flashlight provides 4 lighting modes for different occasions. Prepare your next outdoor activity with the clean and quiet energy from the PHOENIX 200.

KEY FEATURES

Universal Compatibility

Equipped with multiple output ports to power mainstream essential gadgets and small appliances at the push of a button.

Easy Recharging

Conveniently charge the Phoenix 200 through a wall outlet, a car socket, or with a solar panel.

Comprehensive Protection

The battery management system (BMS) enables voltage control, temperature control, short circuit protection, overcurrent protection, and more advanced safety operations.

Powerful Flashlight

Be prepared for blackouts or other emergencies with the multi-mode LED flashlights on both sides of the carrying handle.

General

Dimension	7.1 x 6.1 x 5.6 inch / 181 x 155 x 143 mm
Weight	4.6 lb. / 2.1 kg
LED Flashlight	2 x 1.6W
Battery Capacity	Lithium-ion
Battery Capacity	10.8V, 17500mAh/189Wh

Input

DC Input Port	12-25V, 30W Max
---------------	-----------------

Output

USB-A Port (3)	5V/2.4A Max
USB-C Port	5V/3A Max
CIG Port	9.6-12.6V/10A Max
DC Output Port	9.6-12.6V/5A Max
AC Outlet	110V/60Hz, 150W Rated, 200W Peak
Total	200W Max

